

HAKKO **FX-600**
SOLDERING IRON

For electronics parts such as ICs



For heavy duty

HAKKO **FX-601**
STAINED GLASS

For large components such as
chassis or transformers

to watch a Video of
Amazing heat recovery power

<http://www.hakko.com/english/>

Search



Click!


Replacement tips T18 Series (for FX-600)

* Only the cut surface is solder-tinned.


Units: mm

T18-B Shape B


Standard tip




T18-BL Shape BL




T18-SB Shape SB




T18-S4 Shape S4




T18-C05 Shape 0.5C




T18-C08 Shape 0.8C




T18-C1/T18-CF1* Shape 1C




T18-C2/T18-CF2* Shape 2C




T18-C3/T18-CF3* Shape 3C




T18-C4 Shape 4C,
T18-CF4* Shape 4C




T18-C5 Shape 5C




T18-CF15* Shape 1.5C




T18-CSF25* Shape 2.5CS




T18-S6 Shape S6




T18-D08 Shape 0.8D




T18-D12 Shape 1.2D




T18-D16 Shape 1.6D




T18-D24 Shape 2.4D




T18-D32 Shape 3.2D



T18-DL12 Shape 1.2DL




T18-DL2 Shape 2DL




T18-DL32 Shape 3.2DL




T18-S3 Shape S3




T18-S9 Shape S9




T18-I Shape I



T18-K Shape K




T18-BR02 Shape 0.2BR



Replacement tips T19 Series (for FX-601)


Units: mm

T19-B Shape B




T19-B2 Shape 2B


Standard tip




T19-C3 Shape 3C




T19-C4 Shape 4C




T19-C65 Shape 6.5C




T19-D24 Shape 2.4D




T19-D32 Shape 3.2D




T19-D5 Shape 5D



T19-D65 Shape 6.5D



T19-I Shape I



Replacement Parts

Part No.	Part Name	Specifications
B1785	Nut	For FX-600
B3469	Tip enclosure	
B3720	Tip enclosure with nut	For FX-601
B3694	Knob with screw	For FX-600/FX-601
B3706	Fixing pipe	
B3707	Lock key	

Optional Parts

Part No.	Part Name	Specifications
B3730	Nut and Tip enclosure	Required when converting from FX-601 to FX-600
B3720	Tip enclosure with nut	Required when converting from FX-600 to FX-601
633-01	Iron holder (Cleaning wire type)	For FX-600/FX-601
633-02	Iron holder (Cleaning sponge type)	For FX-600/FX-601

Specifications

Model No.	FX-600	FX-601
Power consumption	50 W (100 V), 59 W (110 V), 74 W (120 V), 43 W (220 V), 47 W (230 V), 51 W (240 V)	47 W (100 V), 56 W (110 V), 67 W (120 V), 42 W (220 V), 46 W (230 V), 50 W (240 V)
Temperature range	200 to 500 °C	240 to 540 °C
Temperature stability	±1 °C at idle temperature	
Tip to ground resistance	< 2 Ω	
Tip to ground potential	< 2 mV	
Heater	Ceramic heater	
Standard tip	Shape B (T18-B)	Shape 2B (T19-B2)
Total length	233 mm (With B tip)	237 mm (With 2B tip)
Total weight	61 g (With B tip)	68 g (With 2B tip)

* Total length and weight values do not include the cord.

* Tip to ground resistance/potential values apply to a grounded type iron only.

**Breakthrough
technology**

Convert to FX-600 or FX-601 using interchangeable parts!

Reduce costs by converting to either model using interchangeable parts (Tip/Tip enclosure/Nut).

HAKKO
HAKKO CORPORATION

HEAD OFFICE

4-5, SHIOKUSA 2-CHOME, NANIWA-KU, OSAKA, 556-0024 JAPAN
TEL:+81-6-6561-3225 FAX:+81-6-6561-8466
http://www.hakko.com E-mail:sales@hakko.com

CA00380EbZa002 2015.10

Specifications and design are subject to change without notice. Copyright HAKKO Corporation. All right reserved.

HAKKO is registered in countries and regions including the following. Japan, USA, South Korea, Singapore, China, the member of CTM.